

ULTRA WIDEBAND ANTENNA FOR MICROWAVE IMAGING USING
MODIFIED FRACTAL STRUCTURE

HAMID MOHAMMED QASEM RASHEDA

A project report submitted in partial fulfillment of the requirements for the award of the
Degree of Master of Electrical Engineering



Faculty of Electrical and Electronic Engineering
Universiti Tun Hussein Onn Malaysia

JULY 2017

Dedicated to,

My beloved father and mother,
MOHAMMED QASEM RASHEDA
and
MASAUDA HUSSAIN ABDULLAH

All my brothers, Sisters and Family

,

My supervisor
Dr. NOORSALIZA BINTI ABDUALLH

My friends.



PTTA UTHM
PERPUSTAKAAN TUNKU TUN AMINAH

ACKNOWLEDGEMENT

In the name of Allah, Most Gracious, Most Merciful. All praises be to Allah, with His permission I have completed the master project of Antenna and hopefully this project will give benefit to others and for my future.

Firstly I would like to give my heartiest gratitude to my supervisor, **Dr. Noorsaliza Binti Abdullah** who has spent a lot of her valuable time to guide me for this project from first week of the semester until last moment before submission. Her advice, guidance, and support will always be my inspiration for the future. I would to thanks her because she has explained to me in details and give a moral supports and excellence idea during my project.

My most grateful and respect to my father, my mother, Whole family and all my friends who are the person in my mind that make me pass through all the hard situation throughout the completion of this project. Finally, I would like to thank everyone that has been involved in this project directly or indirectly for their help and contribution.



ABSTRACT

Since the Federal Communication Commission release of bandwidth of 7.5 GHz (from 3.1 GHz to 10.6 GHz) for ultra wideband application (UWB), UWB is rapidly advancing as a high data rate wireless technology. Moreover, there are more challenges in designing a UWB antenna than a narrow band antenna. A suitable UWB antenna should be capable of operating over an ultra wide bandwidth as allocated by the FCC. In addition, satisfactory radiation properties over the whole frequency range are necessary as well. This project presents the design with fractal geometry of an UWB patch antenna. To achieve UWB characteristic, a planer antenna is considered for the design purpose. The configuration of designed antenna consisted of a partial ground and the patch with addition of two stairs in its bottom edge connected with the feed line. The antenna was designed and optimized using CST Microwave Studio 2014. The proposed antenna is optimized to achieve a fractal shape by introducing slots in the patch at various positions with half grounded structure. A compact design has been observed as a result of optimization. Moreover, the results have been analysed to get the desired bandwidth, and for the comparison purpose the antenna design has been fabricated using FR-4 dielectric substrate and measured its scattering parameters using vector network analyzer (VNA). The obtained results from the measurement have the bandwidth ranges from 2.2 GHz to 12GHz. The analysis of simulated and measured results shows a little deviation due to fabrication and coaxial cable losses.

CONTENTS

TITLE	i
DECLARATION	ii
DEDICATION	iii
ACKNOWLEDGEMENT	iv
ABSTRACT	v
CONTENTS	vi
LIST OF TABLES	viii
LIST OF FIGURES	ix
LIST OF APPENDICES	xi
CHAPTER 1 INTRODUCTION	1
1.1 Research Background	1
1.2 Problem Statement	2
1.3 Objectives of the Project	3
1.4 Scope of the Project	3
1.5 Thesis Outline	3
1.6 Summary	4
CHAPTER 2 LITERATURE REVIEW	5
2.1 Introduction	5
2.2 Previous Work	5
2.3 Ultra Wideband	11
2.4 Ultra Wideband for Medical Application	12
2.5 Ultra Wideband and Monitoring through UWB	14
2.6 Fractal Antenna	16
2.7 Summary	20

CHAPTER 3 RESEARCH METHODOLOGY	21
3.1 Introduction	21
3.2 Proposed Methodology	21
3.3 Design Specification and Calculation	23
3.4 Design Details	28
3.5 Fabrication	36
3.6 Summary	40
 CHAPTER 4 RESULTS AND ANALYSIS	 41
4.1 Introduction	41
4.2 Simulation Results	41
4.3 Radiation Pattern	60
4.4 Current Distribution	62
4.5 Measurement Results	64
4.6 Comparison between Simulated and Measured Designs	70
 CHAPTER 5 CONCLUSION AND RECOMMENDATIONS	 74
5.1 Conclusion	74
5.2 Recommendations	75
 REFERENCES	 76
APPENDIX	80

LIST OF TABLES

TABLE	TITLE	PAGE
3.1	Antenna Specification Design	24
3.2	Calculated Parameter for Design Antenna	28
4.1	Simulation Parameters of Design I	43
4.2	Design Specification for Square Microstrip Patch Antenna	45
4.3	Simulated gain results at different frequency with the efficiency Design I	48
4.4	Simulation Parameters of Design II	52
4.5	Simulated gain results at different frequency with the efficiency Design II	56
4.6	Simulated gain results at different frequency with the efficiency Design III	60

LIST OF FIGURES

FIGURE	TITLE	PAGE
3.1	Project Flow Chart	22
3.2	Parameters List of the Proposed Design	30
3.3	Patch Value of the Proposed Design	30
3.4	Materials Library	30
3.5	Substrate Shape of the Proposed Design	31
3.6	Patch Layout with its Parameters	31
3.7	Feed Line Position in the Patch	32
3.8	Ground Plane with Values of the Proposed Design	32
3.9	Wave Port Structure	33
3.10	Wave Port of the Proposed Design	33
3.11	Time Domain Solver Parameters to Run the Simulation	34
3.12	Strip Feed Line and SMA Connector	35
3.13	Laminating Process	36
3.14	Laminating Machine	37
3.15	UV Exposure Units	37
3.16	Developing Machine	38
3.17	Etching Machine	39
3.18	Stripping Machine	39
3.19	Fabricated UWB Patch Antenna	40
4.1	Top View of the Simulated Design I	43
4.2	Geometry of Square Microstrip Antenna Design I	44
4.3	Simulated Return Loss of Design I	45
4.4	Simulated VSWR of Design I	46
4.5	Simulated Gain at of Design I with different frequency	48
4.6	Simulated Return Loss Graphs with different Length for both Stairs	49

4.7	Simulated Return Loss Graphs with different Width for both Stairs	50
4.8	Simulated Return Loss Curves of the Design I for Feed Line Width	51
4.9	Top View of the 1 st Iteration Simulated Design II	52
4.10	Top View of the Simulated Design II (Proposed Antenna)	53
4.11	Simulated Return Loss of Proposed Design (Design II)	54
4.12	Simulated VSWR of Proposed Design (Design II)	54
4.13	Simulated Gain at different frequency of Proposed Design (Design II)	55
4.14	Top View of the Fractal Array Antenna (Design III)	56
4.15	Simulated Return Loss of Fractal Array (Design III)	57
4.16	Simulated VSWR of Fractal Array (Design III)	58
4.17	Simulated Gain at different frequency of Proposed Design (Design III)	59
4.19	Simulated Radiation Pattern E and H planes at 6 GHz	61
4.20	Simulated Current distribution at 6 GHz all Designs	63
4.21	Fabricated Return Loss of Design I	65
4.22	Fabricated Return Loss of Design II	66
4.23	Fabricated Return Loss of Design III	67
4.24	Measured VSWR of Design I	68
4.25	Measured VSWR of Design II	69
4.26	Measured VSWR of Design III	70
4.27	Comparison between Simulated and measured Design I	71
4.28	Comparison between Simulated and measured of fractal	72
4.29(a)	Comparison between Simulated and measured of fractal array Antenna S11 (Design III)	73
4.29(b)	Comparison between Simulated and measured of fractal array Antenna S22 (Design III)	73

LIST OF APPENDICES

APPENDIX	TITLE	PAGE
A	Antenna Measurement	80
B	Gantt chart	82



PTTA UTHM
PERPUSTAKAAN TUNKU TUN AMINAH

CHAPTER 1

INTRODCUTION

1.1 Research Background

In general, communication plays an important role in human life at present times and the monitoring systems are rapidly changing from being wired to wireless. Still, the telecommunication sector is rapidly growing due to the development of low profile, lightweight and single-feed antennas [1]. Ultra-wideband antenna is defined as an antenna that has a bandwidth greater than 500 megahertz (MHz) and ranges from 3.1 GHz to 10.6 GHz. Instead of sinusoidal waveforms compressed in frequency, ultra-wideband signals are pulse-based waveforms compressed in time. UWB technology has been regarded as one of the most promising wireless technologies for high data rate transmission, higher bandwidth and low power requirements. The difference between a narrowband signal and a UWB signal is that the bandwidth of the UWB signal is much larger than the narrowband, which means UWB signals can operate over wider frequencies [2]. Within this operating range of frequency (3.1 GHz to 10.6 GHz), the antenna should have stable response in terms of impedance matching, gain, radiation pattern polarization, and at the same time it should be of small size, conformal, low cost and should be easily integrated into the RF circuits. The difference between a narrowband signal and a UWB signal is that the bandwidth of the UWB signal is much larger than the narrowband, which means UWB signals can operate over wider frequencies [4, 5]. For that reason, the development in communication systems required the development of low cost, minimal weight and low profile antennas that are capable of maintain high frequency over wide spectrum of frequencies. However, microwave imaging of the application of medical have been received very increasing interest. Moreover, fractal antenna engineering research is a relatively very modern development because significant computing speeds in required to comprehensive the

design [6, 7]. The fractal shapes radiate electromagnetic energy well and have a number of properties that are advantageous over traditional antenna types as it has been discovered. In addition, other advantageous property is that they are compact, meaning that they can occupy a portion of space more efficiently than other antenna types. . While, the most problem of patch antennas in their narrow bandwidth due to surface wave losses and large size of patch for better performance. Fractal geometry allows us to design a small antenna and combine multiple telecommunication services into single device. One of the most applicable developments for wireless devices is reducing size. A small design become an essential for the next generation of antennas for microwave imaging applications which have to integrate multiple services such as medical sector , and radar application and so on . In this condition, we need the smallest fractal antenna to make use of the available in service and for application of the different frequency bands is made possible with wide-band antenna design.

1.2 Problem Statement

Nowadays, the study of fractal antenna has made great progress. Compared with conventional antennas, fractal antennas have more advantages of smaller, multiband as compared to other antennas. However the bandwidth and gain of antenna are considered as the main performance limitation. The narrow bandwidth is mainly due to its resonant nature. With bandwidth as low as a few percent, microwave imaging application using conventional designs are limited. So, in this project the efficient methods used for the enhancement of fractal antenna bandwidth is loading or fractal antenna with two shapes in the patch of the antenna.

This research focus on the enhancement of the gain and bandwidth within the frequency range. Moreover, the study of a geometric fraction concept is as a method to reduce the antenna size is one of the purposes of this project. The effect of material properties on the gain and bandwidth performance of fractal antenna will be investigated.

1.3 Objective of the Project

The following are the objectives of this project:

1. To design an ultra wide band antenna for microwave imaging application using fractal structure.
2. To verify the simulation result with measurement result.

1.4 Scope of the Project

The scope of the project focuses the design of a fractal structured patch antenna to obtain an ultra wideband bandwidth. Addition of stairs at the bottom of patch and the use of reduced ground plane are introduced to obtain the bandwidth. Optimum bandwidths are achieved by varying the width of the slot and its position, stair lengths and widths as well as feed width. The project scopes focusing on four major components which represent as follows:

- 1- Study the characteristic of ultra wideband antennas by means of calculation and simulation.
- 2- Design and model the antenna for Ultra-wide-band (3.1GHz- 10.6 GHz) using CST software.
- 3- Investigate a suitable fractal structure.
- 4- Fabricate and measure the parameters such as S-parameters, radiation pattern and gain after simulation.

1.5 Thesis Outline

In this project, several topics are covered and there are contains in to 4 chapters and the organizations of the chapters are as follows:

The first chapter provides an introduction to antennas, especially the UWB antenna. The problem statement is also presented in this chapter along with the objectives and scope of the project.

The second chapter presents a comprehensive literature review. There will be two types of researches providing a perfect insight about the complete project and its ideas. The fundamental idea on the basic antenna characteristics such as input return loss, radiation pattern, bandwidth, VSWR, input impedance and beam width are discussed. This is followed by discussion of relevant theory and literature review on the designed antenna structures.

The third chapter presents the project methodology and the proposed project antenna design. In addition to that, the components selection and the analytical calculation of the proposed antenna design parameters are presented in detail. The simulation software for analyzing the antenna performance is outlined as well. The fourth chapter presents the design of the proposed antenna design. And it describes the process of design and simulation of a single element antenna. All this results are discussed and also do discussions about the result will be taken.

Chapter four presents the results and analysis of the antenna design. This chapter also elaborated on the results for the whole project as well as frequency response band that is obtained after completing the simulation process. In addition, it covered a detail on the analysis of the result due to fabrication and flowed by measurement testing.

Last chapter is chapter five, where it is on overall conclusion for the project. It is also includes the future works of the projects. The conclusion is related to the project. It is important in order to assure that our objective is achieved

1.6 Summary

In this chapter, the introduction to antenna design and especially fractal antenna is stated. The objectives are clearly identified. The research problem is outlined and justification of the research is evident as well. Justification of the research describes to what extent this research helps to solve the stated problem and benefits the people.

CHAPTER2

LITERATURE REVIEW

2.1 Introduction

This chapter discusses the literature reviews related to this project. The items of discussion are about what other people have done related to the design a fractal antenna for the medical application project. There is also a discussion on the outcome result from other journals, articles and books.

2.2 Previous Work

An Ultra Wideband antenna for portable brain stroke diagnostic system is proposed by A.T. Mobashsher et. al., (2015). Universally, stroke is the most important cause of mature disability. Stroke occurs when the blood supply in a part of brain is disturbed as a blood vessel bursts or is blocked by a clot. Delayed or wrong medical analysis can be fatal for the stroke affected patient. In this paper, a compact antenna is proposed for the brain stroke detection system. However, the proposed antenna is a directional antenna of simple and compacted structure with ultra wideband performance. The antenna exhibits 77% fractional bandwidth with around 5 dBi stable gain and high front to back ratio. All these characteristics are highly required in UWB imaging system. The proposed antenna is utilized in a compact monostatic radar based stroke detection system to investigate a stroke affected realistic head phantom. Lastly, the image is reconstructed using a confocal delay-and-sum algorithm. The imaging results demonstrate the potentiality of using the proposed antenna in a compact stroke diagnostic system which can lead to the final clinical trials [8].

Randouane et al. (2014) proposed the miniaturized UWB microstrip antenna for microwave imaging. The proposed antenna presents an antenna design of a miniaturized microstrip antenna for microwave medical imaging applications which operated from 2.68 GHz to 12.06 GHz using CST. This antenna has designed in order to meet the ultra wideband characteristics in terms of bandwidth and reflection coefficient and for system to detect malignant tumors by microwave imaging. A certain techniques being used of miniaturization and expansion of bandwidth in order to achieve our intention. The antenna has an ordinary rectangular radiating patch, therefore displays a good omnidirectional radiation pattern. Accorded to final structure of our antenna after optimization of various parameters that allow them to expand the bandwidth, with two slots in the patch and slot in the partial ground plane with length of 1.75mm and width of 3mm. This result shows the presence of resonance frequencies at 3.45GHz, 5.97GHz, 7.86GHz and 11.36GHz with a maximum level of S11 parameter at -38.7dB. Bandwidth measured at -10dB ranges from 2.68GHz to 12.06GHz, presenting a width of 9.38GHz [9].

On the design of Tree-type ultra wideband fractal antenna for DS-CDMA system is presented. This paper describes the CPW-feed ultra wideband tree type monopole fractal antenna and its backscattering. The prototype antenna is fabricated with optimized dimension. The antenna exhibits 96.297% impedance bandwidth. To achieve UWB characteristics from 5.825 GHz - 10.6 GHz for DS-CDMA system, the effects of various design parameters have been studied thoroughly. The experimental and simulated results are in good agreement. The effects of various design parameters on impedance bandwidth have also been studied in detail using EM simulator. The nature of H and E – plane radiation patterns are omnidirectional and bidirectional respectively. The measured group delay is almost constant throughout band which is less than 0.75 ns. This indicates the phase linearity. The monostatic RCS of antenna is also simulated iteration-wise for antenna and structural scattering mode. This antenna can be useful for UWB system, Microwave Imaging and vehicular radar and military high data rate wireless communications. The experimental result of proposed antenna exhibits the excellent UWB characteristics from 4.9 GHz to 14.0 GHz at VSWR 2:1. It corresponds to 96.296 % impedance bandwidth. (Raj Kumar and Prem Narayan, 2012).

Sarinka and Manish (2016) proposed an overview on microstrip patch antenna for UWB application from 3.1 – 10.6 GHz band. The commercial wireless devices based on ultra-wideband radio technology (UWB-RT) is widely awaited and anticipated. The Microstrip Patch antenna is the basic element of wireless

communication devices due to its compact size. Ultra wideband microstrip patch antennas are of higher interest because they cover all the WLAN standards. According to federal communications commission (FCC) rules, the 3.1 - 10.6 GHz band is allocated to the ultra wideband (UWB) applications. In this paper, a brief overview on the recent development of small UWB antennas is presented. Several compact and small UWB antennas are exemplified to illustrate their respective performance [16].

A design of microstrip patch antenna using slotted partial ground and addition of stairs and stubs for UWB application is outlined. This paper presents the design with optimum geometry of a novel UWB rectangular patch antenna. A simple narrowband patch antenna is designed before proceeding to the geometry of UWB antenna. A special configuration of patch antenna with slotted partial ground and addition of stairs and stubs was designed and optimized using CST Microwave Studio (CSTMWS). The designed antenna was fabricated, tested and compared with the simulation results. The proposed antenna's characteristics were investigated with various options and found to operate satisfactorily. A remarkable improvement has been noticed in this design. Moreover, the antennas structure offers great advantages due to its simple designs and small dimensions. The designed antenna can operate from 3.2 - 15.7 GHz frequency bands with more than 12 GHz band width with 7.5 dB maximum gain. The return loss is reached up to -40 dB and radiation patterns are acceptable throughout the entire frequency range. In addition, the antenna's structure offers great advantages due to its simple design and small dimensions [13]. (Islam Md et al. 2012).

Design and Optimization of UWB Vivaldi Antenna for Brain Tumor Detection proposed by He Yu et. al., (2016). This paper is designed to detect brain tumor, by transforming the conventional two-layer Vivaldi antenna into a three-layer structure, the cross-polarization effect of antenna is sharply reduced. Based on different conductivity of brain tissues, the microwave absorption effect of brain tumors is analyzed in the end, which indicates the broad prospect of microwave imaging system in the field of tumor detection. In the operating bandwidth, the relative bandwidth is larger than 25%, which meets the needs of ultra wide band. Besides, the return loss is considerably below -10 dB, which means the designed antenna at the feed port is perfectly matched with the transmission line and realizes the goal of low power consumption and high efficiency power transmission. However, the maximum gain of the proposed optimal Vivaldi antenna can reach 7.78 dB at 8.5GHz.

N. Seladji et al. (2012) proposed an UWB bowtie slot antenna for breast cancer detection. In this paper an UWB Bowtie slot antenna with enhanced bandwidth is

suggested. Effects of varying the geometry of the antenna on its performance and bandwidth are studied. The proposed antenna is simulated in CST Microwave Studio. Details of antenna design and simulation results such as return loss and radiation patterns are discussed in this paper. The final antenna structure exhibits good UWB characteristics and has surpassed the bandwidth requirements. The antenna is realized on FR-4 substrate with dielectric permittivity $\epsilon_r = 3.34$ and thickness $h = 0.794\text{mm}$. Its length and width denoted by L and W are respectively 44mm and 24mm . The antenna is fed by a coplanar waveguide, the width of the coplanar lines is $w_a = 1.5\text{mm}$, separated by a distance of 1mm . The first antenna presents a multiband behavior, but the 10 dB return loss bandwidth in the UWB frequency range extends only from 3.63 to 8.31GHz . Whereas it extends from 3.67 to 16.47GHz for the second one, covering the required UWB band. It displays resonant frequencies at 5.65 GHz with S_{11} of -24.7dB , 11.75GHz with S_{11} of -25dB and 15.5GHz with S_{11} of -13dB . This result shows that for the same dimensions of the structure, we can improve the impedance bandwidth of the antenna by rounding antenna's ends [18].

S.Sayi and S.Ramprabhu (2016) proposed a design and fabrication of modified fractal antenna for UWB application. In this paper a modified fractal antenna for bandwidth enhancement. The proposed antenna has stair-slots on the ground plane and cross square fractal element as radiating element. The overall size of the proposed antenna measures $31.35\text{ mm} \times 18.7\text{ mm} \times 1.6\text{ mm}$. The proposed fractal UWB antenna is simulated using CST Microwave Studio. The antenna has broad impedance bandwidth of 8.1 GHz from 2.6 GHz to 10.7 GHz at 8 dB reference level of return loss. The antenna is designed on a low cost FR-4 substrate. The proposed antenna is fabricated and the results are validated using measurements. The proposed antenna may be a useful tool for UWB communication systems. Peak return loss of 36 dB is observed for the proposed antenna. Effects of defected ground planes have been analyzed. The proposed antenna has the advantage of better size reduction suitable for space constraint application. The prototype of the proposed fractal antenna is fabricated and measured. The measured results agree well with the simulated results.

A DGS & DMS Based Hexagonal Fractal Antenna for UWB Applications is presented. This paper proposed a hexagonal shaped fractal monopole antenna is thoroughly investigated for UWB applications. The antenna is mounted on FR4 dielectric substrate and is fed by a 50 ohm microstrip feed line. Basically DGS and DMS structures are introduced to obtain multiband characteristics in UWB frequency range. The simulated results show stable radiation patterns and good return loss of less

than -10 dB in the frequency range of 2.7-9.2 GHz. Each and every modification in the basic structure is supplemented with sufficient simulations and explanation to consolidate the results. (Divyanshu et al. 2012).

A UWB Antenna for Microwave Brain Imaging is proposed by Adhitya Satria et. al., (2016). This paper mentions that Brain tumor is one of degenerative diseases that have been concerned by doctors and researcher to be investigated. MRI, PET, or CT is widely used modalities for brain tumor scanning, which it can provide accurate and high resolution image. However, it costs still relatively high particularly in developing countries with high population like Indonesia. Hence, it is desirable to develop a new brain tumor imaging system that is affordable, easy to operate (portable), non-ionization (safe radiation) and use a non-invasive technique. Microwave imaging is considered as a suitably matched modality to those requirements. In this paper, an UWB antenna is proposed as a transceiver of microwave imaging on brain tumors, which it operates in UWB range (i.e. 3.1–10.6 GHz). The proposed antenna is a printed dipole-like fed by a coplanar waveguide because it provides high frequency response. The antenna is numerically simulated using CST Microwave Studio 2014 and experimentally measured near to a semi-solid head-equivalent phantom, particularly S_{11} and radiation pattern on xy - and yz -plane at 5.8 GHz.

Navid (2016) presented Huygens principle based UWB microwave imaging method for skin cancer detection. Recently, Ultra Wideband (UWB) technology has emerged as a promising alternative for use in a wide range of applications. One of the potential applications of UWB is in healthcare and imaging, motivated by its non-ionizing signals, low cost, low complexity, and its ability to penetrate through mediums. Moreover, the large bandwidth covered by UWB signals permits the very high resolution required in imaging experiments. In this paper, a recently introduced UWB microwave imaging technique based on the Huygens principle (HP), has been applied to multilayered skin model with an inclusion representing a tumor. The methodology of HP permits the capture of contrast such that different material properties within the region of interest can be discriminated in the final image, and its simplicity removes the need to solve inverse problems when forward propagating the waves. Therefore the procedure can identify and localize significant scatterers inside a multilayered volume. Validation of the technique through simulations on multilayered cylindrical model of the skin with inclusion representing the tumor has been performed.

On the Design of CPW-Fed Square Octal Shaped Fractal UWB Antenna is presented. The antenna has been designed on FR4 substrate $\epsilon_r = 4.3$ and thickness 1.53

mm. The antenna has been fabricated and tested using VNA. The experimental results of this antenna offer ultra wide bandwidth from 2.86 GHz to 14.38 GHz. This corresponds to the impedance bandwidth 11.42 GHz and 132.48 %. The experimental results also exhibits the first band from 0.62 GHz to 1.657 GHz corresponds to 1.037 GHz bandwidth. The radiation pattern of this antenna is nearly omni directional. This type of antenna can be used for ultra wide band system, positioning system, microwave imaging and Radar application [15] (Raj Kumar et al. 2012).

Deepshikha et al. (2015) proposed a design of microwave imaging based microstrip Ultra-Wideband Antenna. The designed micro-strip ultra-wideband (UWB) antenna is based on a travelling wave propagating along the tapered surface with a phase velocity less than the speed of light. It results in end-fire radiation with a good penetration and resolution characteristics. The designed antenna for microwave imaging (MI) works on a technique which requires the measurement of reflected electromagnetic waves by the object under test. The UWB antenna with overall size of 70x40x1 mm using Rogers RO3003 substrate with a relative permittivity of 3 is designed using ANSYS-HFSS software. The results for the frequency band 3 to 20 GHz are optimized on the parameters return loss, VSWR and gain. The effect of different medium on the parameters of antenna is also tested. The designed UWB antenna has obtain return loss better than - 10dB and VSWR less than the 1.8 within the band (3GHz to 20GHz). The designed UWB microstrip antenna has wide practical application in concealed weapon detection, medical imaging, remote sensing, through the wall imaging etc.

A microstrip-fed low profile and wideband wide-slot antenna for breast imaging proposed by S. S. Tiang et. al., (2012). This paper presented a novel low profile and wideband wide-slot antenna fed with a microstrip-line. A p-shaped wide slot is printed on a substrate with a compact size of 16 mm x 16 mm and fed by a simple 50 Ω microstrip transmission line. The antenna is designed for microwave breast imaging that cover the ultra-wideband (UWB) frequency band. The design exhibits more than 70% reflection coefficient at 10 dB with stable radiation pattern at the desired bandwidth. The size reduction offers better array ability and well-suited for breast imaging [19].

2.3 Ultra-wideband

Ultra-wideband (UWB) is a new and modern technology with some attractive and very unique features which includes areas of other fields such as wireless communications, radar, and medical engineering. Before 2001, ultra-wideband applications were mainly limited in military areas. But since 2002, The Federal Communication Commission (FCC) has since slowly allowed the use of these commercial bandwidths, and this usage makes it possible that every researchers could benefit the ultra-wideband features. As we have mentioned previously, the Federal Communications Commission (FCC) regulates that the frequency for the ultra-wideband techniques is from 3.1GHz to 10.6GHz in United States of America. However, in Europe, the frequencies include two parts: from 3.4 GHz to 4.8 GHz and 6 GHz to 8.5 GHz. The power radiation requirement of ultra-wideband is strict and it would not disturb the existing equipments because ultra-wide band's spectrum looks like a background noise [4, 20].

2.3.1 Ultra-Wideband Modulation Modes

The ultra-wideband has two modulation modes with respect to available bandwidth or frequency resource: the Multiband OFDM and the Impulse Radio (IR) [21]. These modulation techniques or modes have different advantages and could be applied in different fields in medical area. Multiband OFDM mode of ultra-wideband could be used for small range high speed data communications. For Impulse Radio (IR) mode, by using low-power ultra-short pulses (sub-nanosecond interval), ultra-wideband has many applications such as high resolution penetrating radar in the medical engineering, short-range high-speed broadband access to the Internet, accurate localization at centimetre level. In these applications the accuracy detection and location is much adapt to the medical monitor, and the high resolution imaging is suitable for pathologic imaging, which is modulated by the Impulse Radio (IR). So the ultra-wideband technology has many attracts for conducting many researchers in medical applications area.

2.3.2 Ultra Wideband Medical

Ultra-wideband (UWB) technology is an emerging application trend in medical applications in the new technology. The first time ultra-wideband radar was attempted to use in medical applications in the human body monitoring was in 1993. In 1994, the first US Patent application was filed for medical ultra-wideband radar. A year later, Massachusetts Institute of Technology (MIT) has begun an educational project for the “Radar Stethoscope” [22]. The biomedical use of ultra-wideband radars was better described with photo and sample tracings in 1996, and in the same year the US Patent [23] was awarded, ultra-wideband is often renowned since then to remote sensing and imaging as a possible alternative. So the ultra-wideband in comparison with the X ray imaging and in respect to the human body safety the ultra-wideband radar probes use non-ionizing electromagnetic waves which showed to be harmless to human body. The ultra-wideband radar has very low average power level and is very power efficient which makes it very suitable to medical application. Moreover it is suitable to be a potentially cost effective way of human body screening, especially in real time imaging. By the end of 20th century and in 1999 in particular, many works have begun for ultra-wideband medical applications in cardiology, obstetrics, breath pathways and arteries.

2.4 Ultra-wideband for Medical Application

The ultra-wideband pulses are generated in a very short time period (sub-nanosecond). Because of that its spectrum is below the allowed noise level. This is what makes possible for the ultra-wideband to get Gbps speed by using 10GHz spectrum. For that reason ultra-wideband is suitable to be used for high-speed over short distances. The ultra-short waveforms are generated from the noise-like feature and at the same time does not require IF processing because they can be operated at baseband. This feature is a key advantage for medical engineering [25].

2.4.1 Comparison between Ultra Wideband and Ultrasound

We can compare ultra-wideband to ultrasound. Although ultra-wideband and ultrasound are in fact very similar and many of the signal processing techniques used in ultra-wideband systems can be applied to ultrasonic, only the difference is that the ultrasound has broad applications in many of the latest technologies this time. Ultra-wideband is different because it does not use high frequency sound waves which cannot penetrate obstacles.

In contrast ultrasound is basically a line of sight technology and it is very short range and it is used for medical screening but it typically works only over a few inches. Ultra-wideband impulse of every bit is so many that it can get much higher gain than other popular conventional spread spectrum systems because ultra-wideband uses RF pulses and has high gain. That also explains why ultra-wideband can penetrate through walls. This is what makes ultra-wideband viable for wide area applications where obstacles are certain to be encountered, even though ultrasound may also operate in these kinds of circumstances. The feature makes it easy to image organs of human body for medical application.

2.4.2 High Precision Ranging at the Centimetre Level

One more important feature of ultra-wideband is that it has high precision range at centimetre level based on the ultra-short pulses characteristics. High precision range means strong multi-path (the propagation which results signals reaching the receiving an antenna by two or more paths) resolving capability. The usual and considerate wireless techniques which use continuous wave and the standing time are much longer than multi-path transmission time. The ultra-wideband pulses are much shorter (for 1 nanosecond pulse, the multi-path resolving power equals to 30cm) so it has very strong space resolving and temporal capability, which is suitable for the localization and detection in the medical applications.

2.4.3 Ultra-wideband Electromagnetic Radiation

Yet another important feature of ultra-wideband and perhaps due to the low radio power pulse is the low electromagnetic radiation and these power pulses are less than -41.3dB in indoor environment. This feature which the low radiation of ultra-wideband has little influences on the environment and makes it suitable for hospital applications. So advantage here is that the low radiation is safe for human body even in the short distance which makes it possible to apply ultra-wideband to the clear vision equipments for the ability to gain information about an object, person, location or physical event through human sight senses [26] in the form of extra-sensory perception.

2.5 Medical Screening and Monitoring through UWB

Ultra-wideband is very suitable for the application of medical screening and monitoring. These monitoring applications could be medicine storage monitoring, patient motion monitoring, and the wireless vital signs monitoring of human body.

2.5.1 Ultra-wideband and Patient Motion Monitoring

Ultra-wideband radar can be used in medical field for remote monitoring and measuring the patient's motion and in short distance because of the highly intense pulses used in ultra-wideband technology, this monitoring function could be applied in emergency rooms, home health care, intensive care units, paediatric clinics to alert for the Sudden Infant Death Syndrome SIDIS, rescue operations (to look for some heart beating under ruins, or soil, or snow).

Since ultra-wideband has a short detection range of less than 10 meters, if a large area wanted to be monitored more ultra-wideband sensors will be needed. These sensors using ultra-wideband sub-nanosecond pulses can be motivated for gathering and exchanging a large quantity of sensory data. The energy requirement for these devices is small and is suitable for long time sensing. Bluetooth devices are less suitable for

REFERENCES

- [1] Constantine A. Balanis. (2005). *Antenna Theory Analysis and Design*. Third Edition. Canada: John Wiley & Sons, Inc., Hoboken, New Jersey.
- [2] Fundamentals of Applied Electromagnetics, EE 381 Text Book, Fawwaz T. Ulaby, 2007.
- [3] J.D. Kraus and R.J. Mahefka. *Antenna for All Application*, 3rd Edition, McGraw- Hill
- [4] Federal Communications Commission (FCC), Revision of Part 15 of the Commission's Rules Regarding Ultra-Wideband Transmission Systems, First Report and Order, FCC 02-48, 2002.
- [5] H.G. Schantz, "Ultra Wideband Technology Gains A Boost From New Antennas," *Antenna Systems & Technology*, vol. 4, issue 1, 2001.
- [6] H.G. Schantz, M. Barnes, "The COTAB UWB magnetic slot antenna," *IEEE AP-S International Symposium*, pp.104-107. Boston, USA, July 2001.
- [7] H.G. Schantz. L. Fulleltan, "The Diamond Dipole: A Gaussian Impulse Antenna," *IEEE AP-S International Symposium*, vol.4. pp.100-103, Boston, USA, July 2001.
- [8] Ahmed Toaha et, al. Ultra wideband antenna for portable brain stroke diagnostic system. *2013 IEEE MTT-S International Microwave Workshop Series on RF and Wireless Technologies for Biomedical and Healthcare Applications (IMWS-BIO)*, 2013.
- [9] Radouane KARLI et, al. Miniaturized UWB Microstrip Antenna for Microwave Imaging. *WSEAS TRANSACTIONS on INFORMATION SCIENCE and APPLICATIONS*, E-ISSN: 2224-3402, Vol 11, 2014.
- [10] F. Khan and R. Kumar, "Design and Analysis of Rectangular Microstrip Patch Antenna", *International Journal of Engineering and Advanced Technology*, vol. 2, issue.5, June 2013.
- [11] Gourav Misra et, al. Design and Performance Evaluation of Microstrip Antenna for Ultra-Wideband Applications Using Microstrip Feed. *American Journal of Electrical and Electronic Engineering*, 2015, Vol. 3, No. 4, pp.93-99.

- [12] Indu Bala et. al., Design and Simulation of E-Shape Microstrip Patch Antenna for Wideband Applications. *International Journal of Soft Computing and Engineering (IJSCE)* ISSN: 2231-2307, Vol. 2, No.3, (July 2012) pp.275-280.
- [13] Islam Md. Rafiqul, Zahirul A.A., Feroze Akbar J. Khan and Alkaraki S., Design of Microstrip Patch Antenna Using Slotted Partial Ground And Addition Of Stairs And Stubs For UWB Application, *Cyber Journals: Multidisciplinary Journals in Science and Technology, Journal of Selected Areas in Telecommunications (JSAT)*, May Edition, 2012.
- [14] Lee C.P., Chakrabarty C.K., "Ultra Wideband Microstrip Diamond Slotted Patch Antenna with Enhanced Bandwidth" *Int.J.Communications, Network and System Sciences*, 2011, pp. 468-474.
- [15] Raj Kumar and Prem Narayan Chaubey. On the Design of Tree-type Ultra Wideband Fractal Antenna for DS-CDMA System. *Journal of Microwaves, Optoelectronics and Electromagnetic Applications*, Vol. 11, No.1, June 2012. Pp 107-121.
- [16] Sarinka Sethi and Er. Manish Mehta. Microstrip Patch Antenna for UWB Applications: An Overview. *International Journal of Engineering Science and Computing, June 2016*, vol 6, No.6. pp 7501- 7504.
- [17] Zuhura Juma Ali, "A Printed Microstrip Patch Antenna Design for Ultra Wideband Applications", *International Journal of Science and Research (IJSR)*, Volume 3, Issue 4, , pp. 422-424, April (2014).
- [18] N. Seladji-Hassaine, L. Merad, S.M. Meriah, and F.T. Bendimerad. UWB Bowtie Slot Antenna for Breast Cancer Detection. *International Journal of Medical, Health, and Biomedical, Bioengineering and Pharmaceutical Engineering* Vol: 6, No: 11, 2012
- [19] S.Sayi Soundariyal and S.Ramprabhu. Design and Fabrication of Modified Fractal Antenna for UWB Applications. *IEEE WiSPNET 2016 conference*.pp 1260-1263.
- [20] B. Allen, T. Brown, K. Schwieger, E. Zimmermann, W. Q. Malik, D. J. Edwards, L. Ouvry, and I. Oppermann, "Ultra wideband: applications, technology and future perspectives," in Proc. Int. Workshop Convergent Tech. Oulu, Finland, June 2005.
- [21] Xu Yong, Lu Yinghua, Zhang Hongxin, Wang Yeqiu, " An Overview of Ultra-Wideband Technique Application for Medial Engineering," 2007 IEEE/ICME

- International Conference on Complex Medical Engineering(CME), Beijing, May 2007.
- [22] MIT educational project for the Radar Stethoscope, Massachusetts Institute of Technology, Department of Mechanical Engineering, March 1995.
- [23] T. E. McEwan, "Body monitoring and imaging apparatus and method," US Patent No. 5,573,012, Issued on November 12, 1996.
- [24] Simendra, P. (2004). 'Design and Implementation of Compact Microstrip Fractal Antennas.' Project Report London, Ontario: The University of Western Ontario.
- [25] Xu Yong, Lu Yinghua, Zhang Hongxin, Wang Yeqiu, " An Overview of Ultra-Wideband Technique Application for Medial Engineering ," 2007 IEEE/ICME International Conference on Complex Medical Engineering(CME), Beijing, May 2007.
- [26] Britannica Online Encyclopedia, Retrieved 2007-10-07.
- [27] Enrico M. Staderini, "UWB radars in medicine," IEEE Aerospace and Electronic Systems Magazine, Vol. 17, Issue 1, Page:13-18, 2002
- [28] Ramesh Garg, Prakash Bhartia, Inder Bahl, Apisak Ittipion. (2001) 'Microstrip Antenna Design Handbook.' Artech House.
- [29] Enrico M. Staderini, "UWB radars in medicine," IEEE Aerospace and Electronic Systems Magazine, Vol. 17, Issue 1, Page:13-18, 2002
- [30] P.Felber, (2000). 'Fractal Antennas.' Illinois Institute of Technology.
- [31] Xu Yong, Lu Yinghua, Zhang Hongxin, Wang Yeqiu, " An Overview of Ultra-Wideband Technique Application for Medial Engineering," 2007 IEEE/ICME International Conference on Complex Medical Engineering(CME), Beijing, May 2007.
- [32] K.J Vinoy, (2002), 'Fractal Shapped Antenna Elements for Wide and Multi-band Wireless Application,' Pensylvania State University, PhD Thesis.
- [33] S.Paul (2004) 'Design and Implementation of Compact Microstrip Fractal Antennas' University of Western Ontario London.

- [34] Best, S.R. (2005). 'The Koch Fractal Monopole Antenna: The Significant of Fractal Geometry in Determining Antenna Performance.' Technical Report. Manchester, NH: Cushcraft Corporation.
- [35] Simendra, P. (2004). 'Design and Implementation of Compact Microstrip Fractal Antennas.' Project Report London, Ontario: The University of Western Ontario.
- [36] [S. Haider, "Microstrip patch antennas for broadband indoor wireless system". University of Auckland: Maters Thesis.2003].
- [37] Seok H. Choi, J. K. Kim, J. Y. Park, "A new ultra-wideband antenna for UWB applications," *Microwave and Optical Technology Letters*, Vol. 40, No.5, pp. 399-401, March 2004.
- [38] P.Felber, (2000). 'Fractal Antennas.' Illinois Institute of Technology.
- [39] Pele. I. *et al.* Antenna Design with Control of Radiation Pattern and Frequency Bandwidth. *Antennas and Propagation Society International Symposium*. IEEE. 2004.
- [40] Daniel Valderas et al. Design of UWB Folded-Plate Monopole Antenna Based on TLM. *IEEE Transaction on Antenna and Propagation*. June, 2006. Vol. 54(6).

